

一页 65*65mm 一页,4 折，展开尺寸 260*65mm，英文首页做封面

Instruction Manual

Smart Button



Work with Amazon Alexa

Work with Google Assistant



ZigBee



Scene Setting



Remote Control



Battery Power



Mechanical Push On/Off Button

This Smart Button is powered by battery, which is developed under ZigBee communication. After connecting with ZigBee gateway and adding into Smart life App, it allows you to quickly "set the scene" for a particular room or living scene, like Reading, Movie, and so on.



Smart Button is a time and energy-saving item alternative to the traditional hard-wired switch, with push button design it can be stick on the wall or put it on everywhere you like.

Specification

Product Name:	Smart Button
Model:	IH-K663
Battery:	DC 3V CR2032
Wireless Connection:	ZigBee
Working Range:	25m Open Area
Working Temperature:	0℃→+55℃
Dimension:	Φ50X14mm

Installation

Open the cover then put the button battery in the battery slot.Press the button on the switch, the indicator will turn on, it means that the switch works correctly.



Indicator LED

- Long press the button, the indicator will turn on.
- The indicator flash quickly, it means that the switch under process of network connecting.
- Smart Button Operate: Each one button can be adapted upto three different scenarios through the APP.

Button function

(Single Click) : Activate the 1st scene.
(Double Click) : Activate the 2nd scene.
Press and Hold button 1 for 10s get into pair mode, LEDs will quick flash.



APP Operation

1.Search the App in the store or scan the QR code on the package/manual to download and install the App.

Smart Life

ANDROID APP ON Google Play

Available on the APP Store



2.Register and login

If you download for the first time, please click the "register" button to register your account.If you have an account, click the "login" button.

Log In

Register

3.Network Access Setting

- ZigBee gateway needs to be added before adding devices
- Connect the device to the power supply, press and hold the button to put the device into the network configuration mode, and ensure that the mobile phone is connected to the same network.
- Open the app, on the "smart gateway" page, click "add subdevice", and click "LED already blink".
- Wait for device networking to succeed,Click "DONE" to add the device successfully.

*NOTE: If you fail to add the device, please move the gateway closer to the product and reconnect the network after powering on.